



Power Take Off Alternator Units Range Guide



2 Pole Tractor Driven Generator Range – Full Version

ALTERNATOR + GEARBOX + GUARD + FRAME + PANEL

Industrial, self regulating, synchronous, Regulation +/-4.0% Voltage/Phase: 415/230v / 3 phase or 220/110v 1 phase Alternator, speed/Hz: 3000rpm 50Hz (2 pole)) Duty: Industrial with high starting capacity for electric motors.

MODEL ETC2	50HZ OUTPUT		RPM DRIVEN SHAFT	ESTIMATED	
	1PH KVA	3PH KVA		WEIGHT	HP
ETC 10/2	6.6	10	380rpm	92kg	15
ETC 12.5/2	8.3	12.5	380rpm	98kg	25
ETC 15/2	10	15	435rpm	120kg	30
ETC 19/2	13	19	435rpm	132kg	40
ETC 25/2	16.5	25	435rpm	200kg	50
ETC 30/2	19.8	30	435rpm	210kg	60
ETC 40/2	26.4	40	435rpm	228kg	75

4 Pole Tractor Driven Generator Range – Full Version

ALTERNATOR + GEARBOX + GUARD + FRAME + PANEL

Industrial, self regulating, synchronous, Regulation +/-4.0% Voltage/Phase: 415/230v / 3 phase or 220/110v 1 phase Alternator, speed/Hz: 1500rpm 50Hz (4 pole)) Duty: Industrial with high starting capacity for electric motors.

MODEL ETC4	50HZ OUTPUT		RPM DRIVEN SHAFT	ESTIMATED	
	1PH KVA	3PH KVA		WEIGHT	HP
ETC 15/4	10	15	430rpm	135kg	30
ETC 20/4	13.2	20	430rpm	230kg	40
ETC 25/4	16.5	25	430rpm	245kg	50
ETC 30/4	20	30	430rpm	310kg	60
ETC 35/4	23.1	35	500rpm	325kg	70
ETC 40/4	26.4	40	500rpm	350kg	80
ETC 50/4	33	50	500rpm	365kg	90
ETC 60/4	39.6	60	500rpm	378kg	100
ETC 70/4		70	500rpm	396kg	112
ETC 85/4		85	500rpm	441kg	170

2 Pole Tractor Driven Generator Range Simple Version

ALTERNATOR + GEARBOX + GUARD

Industrial, self regulating, synchronous, Regulation +/-4.0% Voltage/Phase: 415/230v / 3 phase or 220/110v, 1 phase Alternator, speed/Hz: 3000rpm 50Hz (2 pole)) Duty: Industrial with high starting capacity for electric motors.

MODEL ETC4	50HZ OUTPUT		RPM DRIVEN SHAFT	ESTIMATED	
	1PH KVA	3PH KVA		WEIGHT	HP
ETC 30/2	19.8	30	435rpm	210 Kg	60
ETC 40/2	26.4	40	435rpm	210 Kg	75

2 Pole Tractor Driven Welder Range Full Version

WELDING ALTERNATOR INCLUDING PANEL + GEARBOX + GUARD + FRAME

Industrial, self regulating, synchronous, Regulation +/-6.0% Voltage/Phase: 220/110v 1 phase Alternator.

MODEL ETC2	50HZ OUTPUT		RPM DRIVEN SHAFT	ESTIMATED	
	1PH KVA	3PH KVA		WEIGHT	HP
ETC HMI200/2	6	200AC	380rpm	105 Kg	13.5